

CANDY

Idea

CMW 2070M



| | |
|--------------|---------------------------|
| | |
| / | CMW 2070M |
| | 38000119 |
| EAN | 8016361809079 |
| Manufacturer | Candy Hoover Group S.r.l. |
| | MW |
| / | |
| | |
| () | 20 |
| | |
| IoT App | hOn |
| | Standard |
| | 6 |
| | |

| | |
|-----|-----|
| (V) | 230 |
|-----|-----|

| | |
|------|----|
| (Hz) | 50 |
|------|----|



| | |
|--------|--|
| Cavity | |
|--------|--|



| | |
|-----|-----|
| (W) | 700 |
|-----|-----|



| | |
|----------------------------|-----|
| Power consumption Off mode | 0.5 |
|----------------------------|-----|

| | |
|--------------------------------|----------------|
| Power consumption Standby mode | Not applicable |
|--------------------------------|----------------|

| | |
|--|----------------|
| Power consumption Standby mode with info display | Not applicable |
|--|----------------|

| | |
|-------------------------------------|----------------|
| Power consumption Networked Standby | Not applicable |
|-------------------------------------|----------------|

| | |
|---|----|
| Time Off mode/Standby/Standby display/Networked standby | 20 |
|---|----|



| | |
|------|-----|
| (mm) | 245 |
|------|-----|

| | |
|------|-----|
| (mm) | 262 |
|------|-----|

| | |
|--|-----|
| | 452 |
|--|-----|

| | |
|--|-----|
| | 335 |
|--|-----|

| | |
|------|-----|
| (mm) | 294 |
|------|-----|

| | |
|------|-----|
| (mm) | 496 |
|------|-----|

| | |
|------|-----|
| (mm) | 354 |
|------|-----|

| | |
|---|------|
| 0 | 10,5 |
|---|------|

| | |
|---|------|
| 0 | 11,3 |
|---|------|
